

# VOIP2GSM OpenScape Business V2 Template

Internet-Telefonie Service Provider		
Internet-Telefonie Service Provider ändern	Internet-Telefonie Service Provider löschen	Internet-Telefonie-Teilnehmer hinzufügen
Provider-Name: <input type="text" value="VoIP2GSM"/>		
Provider aktivieren: <input checked="" type="checkbox"/>		
Providerbezeichner im System: <input type="text" value="Richtung 12"/>		
Gateway Domain Name: <input type="text" value="sipb3.voip2gsm.de"/>		
Transportprotokoll: <input type="text" value="udp"/>		
Transportsicherheit: <input type="text" value="traditional (udp or tcp)"/>		
Mediensicherheit: <input type="text" value="RTP only"/>		
<b>Provider-Registrar</b>		
Provider Registrar verwenden: <input checked="" type="checkbox"/>		
IP Adresse/Host-Name: <input type="text" value="sipb3.voip2gsm.de"/>		
Port: <input type="text" value="5060"/>		
Reregistration-interval am Provider (s) <input type="text" value="600"/>		
<b>Provider-Proxy</b>		
IP Adresse/Host-Name: <input type="text" value="sipb3.voip2gsm.de"/>		
Port: <input type="text" value="5060"/>		
<b>Provider-Outbound-Proxy</b>		
Provider Outbound-Proxy verwenden: <input type="checkbox"/>		
IP Adresse/Host-Name: <input type="text" value="0.0.0.0"/>		
Port: <input type="text" value="0"/>		
<b>Provider-STUN</b>		
STUN verwenden: <input type="checkbox"/>		
IP Adresse/Host-Name: <input type="text"/>		
Port: <input type="text" value="3478"/>		
<b>Extended SIP Provider Data</b>		
Erweiterte SIP-Provider-Daten anzeigen: <input type="checkbox"/>		
<b>CLIP / CLIR</b>		
CLIP outgoing in From header - display part: <input type="text" value="call number"/>		
CLIP outgoing in From header - user part: <input type="text" value="account"/>		
Outgoing From Header - domain/host part: <input type="text" value="domainName"/>		
Diversion: From contains original CallingPartyNumber: <input type="checkbox"/>		
Diversion: PAI contains original CallingPartyNumber: <input type="checkbox"/>		
CLIP outgoing in P-Asserted-Id header - display part: <input type="text" value="call number"/>		
CLIP outgoing in P-Asserted-Id header - user part: <input type="text" value="call number"/>		
CLIP outgoing in P-Preferred-Id header - display part: <input type="text" value="call number"/>		
CLIP outgoing in P-Preferred-Id header - user part: <input type="text" value="call number"/>		
CLIP outgoing in Diversion header - display part: <input type="text" value="call number"/>		
CLIP outgoing in Diversion header - user part: <input type="text" value="call number"/>		
CLIR outgoing in From header - display part: <input type="text" value="call number"/>		
CLIR outgoing in From header - user part: <input type="text" value="call number"/>		
CLIR outgoing Privacy header: <input type="text" value="user.id"/>		
COLP / TIP supported for outgoing calls: <input type="text" value="COLP supported"/>		

### Call number formatting

Incoming call - Called party number:

Incoming call - Calling party number:

Incoming call - Type of number (calling):

Incoming call - Type of number (called):

Outgoing call - Type of number (calling):

Outgoing call - Type of number (called):

Mapping of provider number:

CLIP no Screening support:

Call No. with international/national prefix:

Called number in E164 format:

Route optimization:

MEX supported:

Contact URI contains:

TCP port used in Contact URI:

### Registration

Register Contact contains IP-Address:

ContactUriWithProtocol:

BNC Registration (SIPconnect):

ReRegistration interval after failure (sec):

ReRegistration mode:

ReRegistration after call failure:

### Miscellaneous

Direct Payload:

Media Renegotiation Avoidance:

Change direction attribute:

UseRouteURIAuthentication:

Ignore 100 Rel:

UseViaRPort:

UPDATE Supported:

P-Early-Media header support:

Session Timer support:

Send automatic 183 response timer (sec):

UDP-Keep Alive:

Keep Alive interval for OPTIONS (sec):

Reregistration on OPTIONS Failure:

Answer to OPTIONS:

### Einrichtung - Wizards - Zentrale Telephonie - Internet-Telefonie

#### Internet-Telefonie-Teilnehmer für VoIP2GSM

Internet-Telefonie-Teilnehmer / Registrierungsnummer:

Autorisierungsname / Telefonie-Benutzername:

Kennwort / Telefonie-Passwort:

Kennwort / Telefonie-Passwort wiederholen:

### Rufnummernzuordnung

Mehrere ITSP-Richtungen:

Standard-Rufnummer:

#### Standard-Rufnummer

ITSP als primärer Amtszugang  
Geben Sie hier eine der Rufnummern ein, die Sie von Ihrem Netzanbieter erhalten haben. Diese Nummer wird bei abgehenden Anrufen als Anrufernummer verwendet, wenn für den jeweiligen Anruf keine andere Rufnummer verfügbar ist.  
Alle von Ihrem Netzanbieter bereitgestellten Rufnummern sollten bei der Leitungs- und Telefonkonfiguration (DuWa-Feld) unter primärer Amtszugang eingetragen werden.